Communications & Power Industries Triode





The Eimac Y-847A is a planar triode specifically designed for high voltage regulator or switch tube (pulse modulator) service. The compact, rugged design has very low internal inductance and capacitance to provide fast rise and fall times in pulse applications. The tube may be mounted in any position and is capable of enduring substantial vibration and shock.

FEATURES:

Maximum plate dissipation: 2,000 Watts

Maximum screen dissipation: ---

Maximum grid dissipation: 2.0 Watts
Frequency for max rating (CW): --- MHz
Amplification factor: 3000 Mu

Filament/cathode: Tungsten Matrix

Voltage: 6.3 Volts Current: 8.4 Amps

Capacitance: Grounded cathode

Input: 25.0 pF
Output: 0.04 pF
Feedthrough: 6.0 pF

Capacitance: Grounded grid

Input: --- pF
Output: --- pF
Feedthrough: --- pF

Cooling: Conduction in oil with

appropriate heat sink

Base: Special, Coaxial with

solder tabs

Air Socket: --Air Chimney: --Boiler: ---

 Length:
 5.60 in; 142.2 mm

 Diameter:
 5.83 in; 148 mm

 Weight:
 5.27 oz; 2.39 kg

BENEFITS:

- Worldwide brand name recognition
- Over 85 years technical expertise

APPLICATIONS:

• Science



RANGE VALUES FOR EQUIPMENT DESIGN			
	Min.	Max.	
Heater Current @ 6.3 Volts	7.4	9.0	A
Interelectrode Capacitances 1 (grounded cathode)			
Cin		28.0	pF
Cout		0.1	pF
Сдр		6.5	pF
Cut-off Bias (Eb = 100 kV, lb = 1.0 mA)		-75.0	Vdc
¹ Capacitance values are for a cold tube as measured in a shie 191.	elded fixture in acc	ordance wit	h Electronic Industries Association Standard RS-

With a history of producing high quality products, we can help you with your triode.

Contact us at MPPMarketing@cpii.com or call us at +1 650-846-2800. The data should be used for basic information only.

Formal, controlled specifications may be obtained from CPI for use in equipment design.



Microwave Power Products Division 811 Hansen Way Palo Alto, California USA 94304 tel +1 650-846-2800 fax +1 650-856-0705 email MPPMarketing@cpii.com web www.cpii.com/MPP For more detailed information, please refer to the corresponding CPI technical description if one has been published, or contact CPI. Specifications may change without notice as a result of additional data or product refinement. Please contact CPI before using this information for system design.